



FEATURES



64MB BIOS

A larger BIOS ROM capacity allows the motherboard to support next-level CPU upgrades with better compatibility.



Back-Connect Design

Move the connectors to the back to provide a cleaner and neater front view and significantly reduces the difficulty of cable management.



Wi-Fi 6E

Supports 6GHz spectrum, MU-MIMO and BSS color technology, delivering speeds up to 2400Mbps.



2.5G LAN

Onboard 2.5G LAN with AI LAN Manager, ensuring a smooth and optimized online experience.



Lightning Gen4 Solution

The Gen4 PCI-E solution with up to 64GB/s bandwidth for maximum transfer speed.



EZ Antenna

EZ Antenna makes the process effortless by simply attaching fasteners to the motherboard without rotation.



EZ PCIe Clip II

Allows for easy removal of the graphics card by pressing the tail-like lock with one finger, even in the cramped case spaces.



M.2 Shield FROZR

Strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.



Extended Heatsink Design

MSI extended PWM heatsink and enhanced circuit design ensures even high-end processors to run in full speed.



Pre-installed I/O Shielding

Better EMI protection and more convenience for installation




Frozr AI Cooling

Detect CPU & GPU temperatures and automatically adjust system fan duty to a proper value.

SPECIFICATIONS

Model Name	PRO B840M-P EVO WIFI6E PZ
CPU Support	Supports AMD Ryzen™ 9000 / 8000 / 7000 series Desktop Processors
CPU Socket	AMD Socket AM5
Chipset	AMD B840 Chipset
Expansion Slots	1 x PCIe 4.0 x16 slot 1 x PCIe 3.0 x4 slot 2 x PCIe 3.0 x1 slots
Display Interface	Support 4K@60Hz as specified in HDMI™ 2.1 - Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR5 - 8000+ MT/s (OC)
Storage	2 x M.2 Gen4 x4 64Gbps slots 1 x M.2 Gen3 x2 16Gbps slot 4 x SATA 6Gbps ports
USB Ports	4 x USB 10Gbps (2 Type-A + 2 Type-C) 4 x USB 5Gbps (4 Type-A) 8 x USB 2.0
LAN	Realtek® 8125 2.5G LAN
Wireless / Bluetooth	Wi-Fi 6E module, Bluetooth 5.3
Audio	8-Channel (7.1) HD Audio with Audio Boost

CONNECTIONS



1. Clear CMOS Button
2. HDMI™
3. USB 10Gbps Type-A
4. USB 2.0
5. 2.5G LAN
6. Wi-Fi / Bluetooth
7. Audio Connectors
8. Flash BIOS Button
9. USB 10Gbps Type-C
10. USB 5Gbps Type-A