# PRO B850-S WIFI6E

BUSINESS FLEGANCE











# **SPECIFICATIONS**

Model Name	PRO B850-S WIFI6E
CPU Support	Supports AMD Ryzen™ 9000 / 8000 / 7000 Series Desktop
	Processors
CPU Socket	Socket AM5
Chipset	AMD B850 Chipset
Expansion Slots	1 x PCle 4.0 x16 slot,
	1 x PCle 4.0 x4 slot,
	1 x PCle 3.0 x1 slot
Display Interface	Support 4K@60Hz as specified in HDMI™ 2.1,
	DisplayPort 1.2 - Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR5 - 8200+ MT/s (OC)
Storage	1 x M.2 Gen5 x4 128Gbps slot,
	1 x M.2 Gen4 x4 64Gbps slot,
	4 x SATA 6Gbps ports
USB ports	5 x USB 10Gbps (3 Type-A + 2 Type-C),
	6 x USB 5Gbps (6 Type-A)
	4 x USB 2.0
LAN	Realtek® 8125 2.5G LAN
WiFi / BT	Wi-Fi 6E Solution, Bluetooth 5.3
Audio	8-Channel (7.1) HD Audio with Audio Boost

# **FEATURES**



#### **5G Network Solution**

Featuring premium 5G LAN to deliver better network experience.



#### **Lightning Gen 5 Solution**

The latest Gen 5 M.2 solution with up to 128GB/s bandwidth for maximum transfer speed.



#### **EZ Antenna**

EZ Antenna makes the process effortless by simply attaching fasteners to the motherboard without rotation.



#### EZ PCIe Clip II

Allows for easy removal of the graphics card by pressing the taillike lock with one finger, even in the cramped case spaces.



#### 2.5G Network Solution

Featuring premium 2.5G LAN to deliver better network experience.



### Latest DDR5 Memory

A huge step of DDR performance enhancement with the latest DDR5 memory and MSI Memory Boost technology.



#### /i-Fi 6E

The latest wireless solution supports 6GHz spectrum, MU-MIMO and BSS color technology, delivering speeds up to 2400Mbps.



### Frozr Al Cooling

Detect CPU & GPU temperatures and automatically adjust system fan duty to a proper value.



# **EZ Debug LED**

Easiest way to troubleshoot.



## **Memory Boost**


Advanced technology to deliver pure data signals for the best performance, stability and compatibility.



# Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.

# **CONNECTIONS**



- 1. Clear CMOS Button
- 3. 2.5G LAN
- 5. USB 5Gbps Type-A
- 7. Audio Connectors
- 9. HDMI™
- 11. USB 10Gbps Type-C
- 2. DisplayPort
- 4. USB 10Gbps Type-A
- 6. Wi-Fi / Bluetooth
- 8. Flash BIOS Button
- 10. USB 10Gbps Type-A