



## FEATURES

## SPECIFICATIONS

<b>Number of Fans</b>	3
<b>Fan Dimensions</b>	120 x 120 x 25mm / 4.7 x 4.7 x 0.98 inches
<b>Fan Speed</b>	500 ~ 2000 RPM
<b>Fan Power Consumption</b>	1.8 W
<b>Fan Rated Current</b>	0.15 A
<b>Fan Rated Voltage</b>	12V DC
<b>Fan Bearing</b>	Two Ball Bearing
<b>Fan Air Pressure</b>	0.23 ~ 2.39 mmH2O
<b>Fan Noise Level</b>	14.3 ~ 34.3 dBA
<b>Fan Air Flow</b>	21.63 ~ 78.73 CFM
<b>Fan Lighting</b>	ARGB
<b>Fan ARGB Cable Connector</b>	Pin + Socket
<b>PWM Mode</b>	Yes
<b>Fan Cable Length (5V ARGB / PWM cable)</b>	550 / 350mm; 21.65 / 13.78 inches
<b>Radiator Material</b>	Aluminum
<b>Radiator Dimensions</b>	394 x 120 x 27mm / 15.5 x 4.7 x 1.06 inches
<b>Radiator Water Cooling Pipe Length</b>	400mm / 15.75 inches
<b>Block Dimensions</b>	80.57x 66.82 x 48.58mm / 3.17 x 2.63 x 1.91 inches
<b>Block Lighting</b>	ARGB
<b>Block ARGB 5V Cable Length</b>	400mm / 15.75 inches
<b>Block ARGB Cable Connector</b>	Pin + Socket
<b>Pump Load Current</b>	0.34 A
<b>Pump Rated Voltage</b>	12V DC
<b>Pump Speed</b>	4200±10%RPM
<b>Pump Power Consumption</b>	4.08W
<b>Intel Socket</b>	LGA 1150/1151/1155/1156/1200 LGA 1366/2011/2011-3/2066
<b>AMD Socket</b>	AM4/FM2+/FM2/FM1/AM3+/AM3/AM2+/AM2 SocketTR4/sTRX4/SP3
<b>AMD SocketTR4 / sTRX4 / SP3 Socket</b>	Y
<b>Accessories</b>	1 to 3 Fan PWM cable x 1 PSU Molex 4-Pin to 4-Pin(2 Pin Wired) Fan cable x 1 Noise reducer cable x 1