

# **MPG X570 GAMING PLUS**

GAME IN STYLE





# **SPECIFICATIONS**

Model Name	MPG X570 GAMING PLUS
CPU Support	Supports 2nd and 3rd Gen AMD Ryzen™ / Ryzen™ with
	Radeon™ Vega Graphics and 2nd Gen AMD Ryzen™ with
	Radeon™ Graphics Desktop Processors
CPU Socket	Socket AM4
Chipset	AMD® X570 Chipset
Graphics	2 x PCI-E 4.0 x16 slots
Interface	Supports 2-Way AMD® CrossFire™ Technology
Display Interface	HDMI™ - Requires Processor Graphics
Memory Support	4 DIMMs, Dual Channel DDR4-4400(OC)
<b>Expansion Slots</b>	3x PCIe 3.0 x1 slots
Storage	1 x Lightning M.2 slot (Gen4 x4) + 1 x Turbo M.2 slot (Gen3
	x4)
	6 x SATA 6Gb/s
USB Ports	2 x USB 3.2 (Gen2, A+C) + 8 x USB 3.2 (Gen1) + 6 x USB
	2.0
LAN	Realtek® RTL8111H Gigabit LAN
Audio	8-Channel(7.1) HD Audio with Audio Boost 4

### **FEATURES**



### Frozr Heatsink Design

Designed with the patented fan and double ball bearings to provide best performance for enthusiast gamers and prosumers.



#### **Audio Boost 4**

Isolated audio with a high quality audio processor for the most immersive gaming experience.



### Flash BIOS Button

Simply use a USB key to flash any BIOS within seconds, without installing a CPU, memory or graphics card.



### **Lightning Gen4 Solution**

The latest Gen4 PCI-E and M.2 solution with up to 64GB/s bandwidth for maximum transfer speed.



#### **Core Boost**

With premium layout and fully digital power design to support more cores and provide better performance.



## M.2 Shield FROZR

M.2 thermal accessory keeps M.2 SSDs safe while preventing throttling, making them run faster.



### **Extended Heatsink Design**


MSI extended PWM heatsink and enhanced circuit design ensures even high-end processors to run in full speed.



### **DDR4 Boost**

Advanced technology to deliver pure data signals for the best gaming performance and stability.

## CONNECTIONS



- 1. Keyboard / Mouse
- 3. LAN
- 5. Flash BIOS Button
- 7. HDMI™
- 9. USB 3.2 Gen1 Type-A
- 2. USB 3.2 Gen1 Type-A
- 4. Audio Connectors
- 6. USB 2.0
- 8. USB 3.2 Gen2 Type-A + C
- 10. Optical S/PDIF out