



# msi

CARTES MÈRES

## MEG Z390 GODLIKE

MAÎTRISEZ LA CONCURRENCE



## SPECIFICATIONS

<b>Modèle</b>	MEG Z390 GODLIKE
<b>Processeur</b>	Support des processeurs Intel® Core™ de 8ème et 9ème génération / Pentium® Gold / Celeron®
<b>Socket</b>	LGA 1151
<b>Chipset</b>	Intel® Z390
<b>Interface graphique</b>	4 x PCI-E 3.0 x16 Support NVIDIA® SLI™ 2 way et AMD® CrossFire™ 4 way
<b>Mémoire</b>	4 DIMM, Dual Channel DDR4-4600 (OC)
<b>Slots d'extension</b>	1 x PCI-E x1
<b>Stockage</b>	3 x Turbo M.2 (compatible Intel® Optane™ Memory) 1 x Turbo U.2 6 x SATA 6 Gb/s
<b>Ports USB</b>	6 x USB 3.1 (Gen2, A+C) + 6 x USB 3.1 (Gen1) + 4 x USB 2.0
<b>LAN</b>	2 x Killer™ E2500 Gigabit Ethernet
<b>Wireless / BT</b>	Killer™ Wireless-AC 1550
<b>Audio</b>	HD 8 canaux (7.1) avec DAC XTREME AUDIO /dd>
<b>Format</b>	E-ATX

## FEATURES



### Game Boost

One second automated overclocking. Turn the dial and your PC gets another adrenalin shot.



### Killer xTend

Combine a built-in-switch with wireless extender. Killer fueled LAN & WIFI extender with ultimate traffic prioritization.



### Xtreme Audio DAC

Isolated audio with ESS DAC, 2x audio processors & Nahimic to deliver the breathtaking sound quality with 6.3mm headphone 384kHz/32-bit.



### Core Boost

Circuit repensé et alimentation numérique pour supporter plus de cœurs et assurer de meilleures performances.



### Panneau E/S préinstallé

Les entrées et sorties sont mieux protégées contre les ondes électromagnétiques et l'installation est simplifiée.



### M.2 Shield Frozr

La solution M.2 Shield Frozr intégrée est pensée pour garder les SSD M.2 à bonne température et empêcher le phénomène de throttling.



### Mystic Light Infinity

Personalize your PC with 16.8 million colors / 29 effects with MSI Mystic Light APP, making your system come alive with infinity.



### Dynamic Dashboard


Built-in dynamic panel that indicates the status of GODLIKE and shows off your own personality.



### Dual Front Type-C USB 3.1 Gen2

Powered by USB 3.1 Gen2, compatible with the latest PC chassis and perfect for external drives and other mobile devices.

## CONNECTIONS



- |                                |  |
|--------------------------------|--|
| 1. Bouton Clear CMOS           | 2. Connecteur antenne Wi-Fi /Bluetooth |
| 3. Port PS/2 GAMING Device     | 4. Double Killer™ E2500 Gigabit LAN    |
| 5. Connecteurs audio HD        | 6. Flash BIOS Button                   |
| 7. Ports USB 3.1 Gen1          | 8. Ports USB 3.1 Gen2                  |
| 9. Ports USB 3.1 Gen2 type A+C | 10. Jack casque 6                      |
| 11. 3 mm                       | 12. Sortie S/PDIF optique              |