



## SPECIFICATIONS

<b>Model Name</b>	MEG X399 CREATION
<b>CPU Support</b>	Supports AMD® Ryzen™ THREADRIPPER™ Series Processors
<b>CPU Socket</b>	SocketTR4
<b>Chipset</b>	AMD® X399 Chipset
<b>Graphics Interface</b>	4 x PCI-E 3.0 x16 slot, Supports 3-way NVIDIA® SLI™ / 3-way AMD® CrossFire™
<b>Memory Support</b>	8 DIMMs, Quad Channel DDR4-3600+(OC)
<b>Expansion Slots</b>	1 x PCI-E x1 slot
<b>Storage</b>	3 x Turbo M.2 slots 8 x SATA 6Gb/s
<b>USB ports</b>	1 x USB 3.1 Gen 2 front Type C 14 x USB 3.1 Gen 1 (1 x rear Type C) 4 x USB 2.0
<b>LAN</b>	2 x Intel® I211 Gigabit LAN, Intel® WIFI AC 9260
<b>Audio</b>	8-Channel(7.1) HD Audio with Audio Boost 4
<b>Form Factor</b>	E-ATX

## FEATURES



### Dual 8 Pin power supply

By providing dual 8 pin connectors to ensure adequate power supply to unleash ultimate multi-core CPU performance.



### Flash BIOS Button

Simply use a USB key to flash any BIOS within seconds, without installing a CPU, memory or graphics card.



### MYSTIC LIGHT and SYNC

Personalize your PC with 16.8 million colors / 17 effects, controlled in one click!



### Triple Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.



### MULTI-GPU

With Steel Armor PCI-E slot, Supports 3-way NVIDIA® SLI™ / 3-way AMD® CrossFire™



### M.2 Shield FROZR

Strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.



### Core Boost

With premium layout and optimized power design to support more cores and provide better performance.

## CONNECTIONS



1. Clear CMOS Button
2. USB 3.1 Gen1 Ports
3. USB 3.1 Gen1 Ports
4. Intel® WiFi/ Bluetooth Module
5. Dual Intel® LAN Ports
6. HD Audio Connectors
7. Flash BIOS Button
8. USB 3.1 Gen1 Ports
9. AMD Turbo USB 3.1 Gen 1 Type A + C
10. Optical S/PDIF-Out