

msi







# **SPECIFICATIONS**

Model Name	B850M GAMING WIFI
CPU Support	Supports AMD Ryzen <sup>™</sup> 9000 / 8000 / 7000 Series Desktop
	Processors
CPU Socket	AMD Socket AM5
Chipset	AMD B850 Chipset
Expansion slots	1 x PCle 5.0 x16 slot
	1 x PCle 4.0 x4 slot
Display Interface	Support 4K@60Hz as specified in HDMI <sup>™</sup> 2.1,
	DisplayPort 1.4 - Requires Processor Graphics
Memory Support	2 DIMMs, Dual Channel DDR5 - 8200+ MT/s (OC)
Storage	1 x M.2 Gen5 x4 128Gbps slot,
	1 x M.2 Gen4 x4 64Gbps slot,
	4 x SATA 6Gbps ports
USB ports	1 x USB 10Gbps (1 Type-C)
	6 x USB 5Gbps (5 Type-A + 1 Type-C)
	6 x USB 2.0
LAN	Realtek® 8126-VB 5G LAN
Wireless / BT	Wi-Fi 7 module, Bluetooth 5.4
Audio	8-Channel (7.1) HD Audio with Audio Boost

## **FEATURES**

# GEN5

### Lightning Gen 5

The latest PCIe 5.0 solution with up to 128GB/s bandwidth for maximum transfer speed.



#### **Dual M.2 Connectors**

Onboard 2x M.2 Connectors with one PCIe 5.0 solution, strengthened by M.2 Shield Frozr.



# M.2 Shield FROZR

Strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.



#### EZ PCIe Clip II

Allows for easy removal of the graphics card by pressing the tail-like lock with one finger, even in the cramped case spaces.



### Pre-installed I/O Shielding

Better EMI protection and more convenience for installation



#### Latest DDR5 Memory

A huge step of DDR performance enhancement with the latest DDR5 memory and MSI Memory Boost technology.



## Wi-Fi 7

Wi-Fi 7 is the latest wireless solution that takes a huge leap forward with multiple improvements to meet the traffic demand brought and the growing number of wireless devices.



# **5G Network Solution**


Featuring premium 5G LAN to deliver better network experience.



## Audio Boost

Reward your ears with studio grade sound quality for the most immersive audio experience.

# **CONNECTIONS**



- 1. Display Port
- 3. USB 5Gbps (Type-A)
- 5. 5G LAN
- 7. USB 5Gbps (Type-C)
- 9. USB 2.0
- 11. Audio Connectors
- 2. HDMI™
- 4. Clear CMOS Button
- 6. Wi-Fi / Bluetooth
- 8. Flash BIOS Button
- 10. USB 5Gbps (Type-A)