



## FEATURES



### PCI-E Steel Armor

Protecting VGA cards against bending and EMI



### Mystic Light Extension

Control additional RGB strips or other RGB components added to your system with Mystic Light APP and mobile device.



### M.2 Shield FROZR

Strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.



### Lightning Gen4 Solution

The latest Gen4 PCI-E and M.2 solution with up to 64GB/s bandwidth for maximum transfer speed.



### Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.



### EZ Debug LED

Easiest way to troubleshoot.



### Audio Boost

Reward your ears with studio grade sound quality for the most immersive audio experience.



### DDR4 Boost

Advanced technology to deliver pure data signals for the best gaming performance and stability.




### 2oz Thickened Copper PCB

An enhanced PCB design improves heat dissipation and performance reliability.

## SPECIFICATIONS

<b>Model Name</b>	B550-A PRO
<b>CPU Support</b>	Support for 3rd Gen AMD® Ryzen™ processors and future AMD® Ryzen™ processors with BIOS update
<b>CPU Socket</b>	AMD Socket AM4
<b>Chipset</b>	AMD® B550 Chipset
<b>Graphics Interface</b>	1x PCIe 4.0 / 3.0 x16 slot + 1x PCIe 3.0 x16 slot
<b>Display Interface</b>	Support 2-way AMD® CrossFire™ Technology
<b>Memory Support</b>	DisplayPort, HDMI™ – Requires Processor Graphics
<b>Expansion Slots</b>	4 DIMMs, Dual Channel DDR4-4400 MHz (OC)
<b>Storage</b>	2x PCI-E 3.0 x1 slots
<b>USB ports</b>	1x M.2 Gen4 x4, 1x M.2 Gen3 x4 slot
	6x SATA 6Gb/s ports
	2x USB 3.2 Gen 2 10Gbps (1 Type-A + 1 Type-C)
	+ 5x USB 3.2 Gen 1 5Gbps (4 Type-A+ 1 Type-C)
	+ 8 x USB 2.0
<b>LAN</b>	Realtek® RTL8111H Gigabit LAN
<b>Audio</b>	8-Channel (7.1) HD Audio with Audio Boost

## CONNECTIONS



1. Keyboard / Mouse
2. DisplayPort
3. LAN
4. HD Audio Connectors
5. Flash BIOS Button
6. USB 2.0
7. HDMI™
8. USB 2.0
9. USB 3.2 Gen 1 5Gbps Type-A
10. USB 3.2 Gen 2 10Gbps Type-A+C