MEG Z390 GODLIKE

ОДНО УСТРОЙСТВО ПОКОРИТ ВСЕХ...







SPECIFICATIONS

Наименование	MEG Z390 GODLIKE
модели	
Поддерживаем	Поддерживаются процессоры 9-го / 8-го поколения Intel®
ые процессоры	Core™ / Pentium® Gold / Celeron®
Сокет	LGA 1151
Чипсет	Intel® Z390
Графические	4 x PCI-E 3.0 x16 слота
интерфейсы	Поддерживаются технология 2-way NVIDIA® SLI™ и технология 4-way AMD® CrossFire™
Поддерживаем	4 слота DIMM, двухканальные модули памяти
ая память	DDR4-4600(OC)
Слоты	1 x PCI-E x1 слот
расширения	
Накопители	3 x Turbo M.2 слота (поддерживается память Intel®
	Optane™)
	1 x Turbo U.2
	6 x SATA 6Γ6/c
USB порты	6 x USB 3.1 (Gen2, A+C) + 6 x USB 3.1 (Gen1) + 4 x USB
	2.0
LAN сеть	2 x Killer™ E2500 Gigabit Ethernet
Wireless / BT	Killer™ Wireless-AC 1550
Звук	8-кан. (7.1) HD Audio с XTREME AUDIO ЦАП
Форм фактор	E-ATX

FEATURES



Mystic Light Infinity

Personalize your PC with 16.8 million colors / 29 effects with MSI Mystic Light APP, making your system come alive with infinity.



Dynamic Dashboard

Built-in dynamic panel that indicates the status of GODLIKE and shows off your own personality.



Pre-installed I/O Shielding

Better EMI protection and more convenience for installation



M.2 SHIELD FROZR

Onboard M.2 thermal solution to keep M.2 SSDs safe while preventing throttling, making them run cooler & faster.



One second automated overclocking. Turn the dial and your PC gets another adrenalin shot.



Killer xTend

Combine a built-in-switch with wireless extender. Killer fueled LAN & WIFI extender with ultimate traffic prioritization.



Xtreme Audio DAC

Isolated audio with ESS DAC, 2x audio processors & Nahimic to deliver the breathtaking sound quality with 6.3mm headphone 384kHz/32-bit.



Dual Front Type-C USB 3.1 Gen2

Powered by USB 3.1 Gen2, compatible with the latest PC chassis and perfect for external drives and other mobile devices.



Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.

CONNECTIONS



- 1. Clear CMOS Button
- 3. PS/2 GAMING Device Port
- 5. HD Audio Connectors
- 7. USB 3.1 Gen1 Ports
- 9. USB 3.1 Gen2 Ports Type-A+C
- 11. Optical S/PDIF-Out
- 2. Wi-Fi /Bluetooth Antenna Connectors
- 4. Double Killer™ E2500 Gigabit LAN
- 6. Flash BIOS Button
- 8. USB 3.1 Gen2 Ports

10. 6.3mm headphone