GAME IN STYLE



SPECIFICATIONS

| Model Name | X470 GAMING PRO CARBON AC |
|------------------------|---|
| CPU Support | Supports AMD® RYZEN™ Desktop processors and |
| | A-series / Athlon™ Processors for Socket AM4 |
| CPU Socket | AM4 |
| Chipset | AMD® X470 Chipset |
| Graphics | 2 x PCI-E 3.0 x16 slots + 1 x PCI-E 2.0 x16 slot, |
| Interface | Supports 2-way SLI / 3-way CrossFire |
| Display Interface | DisplayPort, HDMI™ - Requires Processor Graphics |
| Memory Support | 4 DIMMs, Dual Channel DDR4-3466MHz+(OC) |
| Expansion Slots | 2 x PCI-E x1 slots |
| Storage | 2 x M.2 slots |
| | 8 x SATA 6Gb/s |
| USB ports | 2 x USB 3.1 (Gen2, A+C) + 8 x USB 3.1 (Gen1) |
| | 6 x USB 2.0 |
| LAN | Intel® I211AT Gigabit LAN |
| Wi-Fi / BT | Intel® Wireless-AC 3168, Bluetooth 4.2 |
| Audio | 8-Channel(7.1) HD Audio with Audio Boost |
| Form Factor | ATX |

FEATURES



MYSTIC LIGHT and SYNC

Personalize your PC with 16.8 million colors / 17 effects, controlled in one click!



AMD Turbo USB 3.1 Gen2

Powered by AMD, ensure an uninterrupted connection with more stability and fastest USB speeds.



Dual 8 Pin power supply

By providing dual 8 pin connectors to ensure adequate power supply to unleash ultimate multi-core CPU performance.



Isolated audio with a high quality audio processor for the most immersive gaming experience.



DDR4 Boost with Steel Armor

Fully isolated and shielded DIMM slots to deliver pure data signals for the best gaming performance and stability.



Game Boost

One second automated overclocking. Turn the dial and your PC gets another adrenalin shot.



Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.



EZ Debug LED

Easiest way to troubleshoot.



Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.

CONNECTIONS



- 1. PS/2 Combo Port
- 3. Wi-Fi / Bluetooth
- 5. LAN Port
- 7. USB 2.0
- 9. Clear CMOS button
- 11. Optical S/PDIF OUT
- 2. DisplayPort
- 4. USB 3.1 Gen1
- 6. Golden Audio Connectors
- 8. HDMI™ Port
- 10. USB 3.1 Gen2