# **B850M GAMING WIFI6E**

WIN THE COMPETITION









## **SPECIFICATIONS**

| Model Name        | B850M GAMING WIFI6E                                   |
|-------------------|---|
| CPU Support       | Supports AMD Ryzen™ 9000 / 8000 / 7000 Series Desktop |
|                   | Processors  |
| CPU Socket        | AMD Socket AM5  |
| Chipset           | AMD B850 Chipset                                      |
| Expansion slots   | 1 x PCle 4.0 x16 slot, 1 x PCle 3.0 x1 slot           |
| Display Interface | Support 4K@60Hz as specified in HDMI™ 2.1,            |
|                   | DisplayPort 1.4 - Requires Processor Graphics         |
| Memory Support    | 2 DIMMs, Dual Channel DDR5 - 8200+ MT/s (OC)          |
| Storage           | 1 x M.2 Gen5 x4 128Gbps slot,                         |
|                   | 1 x M.2 Gen4 x4 64Gbps slot,                          |
|                   | 4 x SATA 6Gbps ports                                  |
| USB ports         | 1 x USB 10Gbps (1 Type-C)                             |
|                   | 6 x USB 5Gbps (1 Type-C + 5 Type-A)                   |
|                   | 6 x USB 2.0   |
| LAN               | Realtek® 8125 2.5G LAN                                |
| WIFI / BT         | Wi-Fi 6E module, Bluetooth 5.3                        |
| Audio             | 8-Channel (7.1) HD Audio with Audio Boost             |

## **FEATURES**



#### **64MB BIOS**

A larger BIOS ROM capacity allows the motherboard to support next-level CPU upgrades with better compatibility.



### **Lightning Gen 5 Solution**

The latest Gen 5 M.2 solution with up to 128GB/s bandwidth for maximum transfer speed.



## **Extended Heatsink Design**

MSI extended PWM heatsink and enhanced circuit design ensures even high-end processors to run in full speed.



#### M.2 Shield FROZE

Strengthened built-in M.2 thermal solution. Keeps M.2 SSDs safe while preventing throttling, making them run faster.



#### Z PCIe Clip I

Allows for easy removal of the graphics card by pressing the tail-like lock with one finger, even in the cramped case spaces.



#### **EZ Antenna**

EZ Antenna makes the process effortless by simply attaching fasteners to the motherboard without rotation.



### **PCI-E Steel Armor**

Protecting VGA cards against bending and EMI.



### Wi-Fi 6E

Supports 6GHz spectrum, MU-MIMO and BSS color technology, delivering speeds up to 2400Mbps.



## 2.5G Network Solution


Featuring premium 2.5G LAN to deliver better network experience.



### **Audio Boost**

Reward your ears with studio grade sound quality for the most immersive audio experience..

# **CONNECTIONS**



- 1. Clear CMOS Button
- 3. 2.5G LAN
- 5. Audio Connectors
- 7. HDMI™
- 9. USB 5Gbps (Type-C)
- 2. USB 5Gbps (Type-A)
- 4. Wi-Fi / Bluetooth
- 6. Display Port
- 8. Flash BIOS Button
- 10. USB 2.0