



## SPECIFICATIONS

<b>Model Name</b>	Z370 GAMING M5
<b>CPU Support</b>	Supports 9 <sup>th</sup> / 8 <sup>th</sup> Gen Intel® Core™ / Pentium® Gold / Celeron® processors for LGA 1151 socket
<b>CPU Socket</b>	LGA 1151
<b>Chipset</b>	Intel® Z370 Chipset
<b>Graphics</b>	3 x PCI-E 3.0 x16 slots
<b>Interface</b>	2-way SLI / 3-way CrossFire
<b>Display Interface</b>	DisplayPort, HDMI™
<b>Memory Support</b>	4 DIMMs, Dual Channel DDR4-4000(OC)
<b>Expansion Slots</b>	3 x PCI-E x1 slots
<b>SATA / M.2 / U.2</b>	6 x SATA 6Gb/s ports, 2 x Turbo M.2 slots
<b>USB 3.1 Gen2</b>	2 x USB 3.1 Gen2 (Type A+C)
<b>USB 3.1 Gen1</b>	6 x USB 3.1 Gen1
<b>USB 2.0</b>	7 x USB 2.0
<b>LAN</b>	Killer™ E2500 Gigabit LAN with Killer Network Manager
<b>Audio</b>	7.1 Channel High Definition Audio with Audio Boost 4
<b>Form Factor</b>	ATX

## FEATURES



### Mystic Light RGB LED

Personalize your PC with 16.8 million colors / 17 effects, controlled in one click!



### Twin Turbo M.2 with M.2 Shield v2

Two Turbo M.2 slots for PCI-E Gen3 x4 NVMe M.2 SSDs with onboard M.2 thermal solution to prevent throttling.



### Lightning USB 3.1 Gen2

Powered by the ASMedia ASM3142 USB 3.1 Gen2 controller, Lightning USB offers the fastest USB speeds up to 10 Gb/s.



### Audio Boost 4 with Nahimic

Isolated audio with a high quality HIFI audio processor and amplifier for the most immersive gaming experience.



### Killer LAN

Get ready for the lowest latency with Killer's exclusive network management for gaming traffic prioritization.



### DDR4 Boost with Steel Armor

Fully isolated and shielded DIMM slots to deliver pure data signals for the best gaming performance and stability.



### MULTI-GPU

With Steel Armor PCI-E slot. Supports 2-Way AMD Crossfire™.



### VR Ready

Automatically optimizes your system for VR usage, pushing for maximum performance.



### EZ Debug LED

Easiest way to troubleshoot.

## CONNECTIONS



1. PS/2 GAMING Device Port
2. USB 2.0 Port
3. DisplayPort
4. LIGHTNING USB 3.1 Gen2 Type-A
5. Killer™ E2500 Gigabit LAN
6. HD Audio Connectors
7. USB 2.0 Port
8. Clear CMOS Button
9. HDMI™
10. LIGHTNING USB 3.1 Gen2 Type-C
11. VR Ready USB 3.1 Gen1 Ports
12. Optical S/PDIF-Out