



## SPECIFICATIONS

Model Name	Z370 TOMAHAWK
CPU support	Supports 8th Gen Intel® Core™ i3/i5/i7 processors, and Intel® Pentium® and Celeron® processors
CPU socket	LGA 1151
Chipset	Intel® Z370 Chipset
Graphics Interface	3 x PCI-E 3.0 x16 slots 2-way CrossFire
Display Interface	DVI-D, HDMI™
Memory support	4 DIMMs, Dual Channel DDR4-4000(OC)
Expansion slots	3 x PCI-E x1 slots
SATA / M.2 / U.2	6 x SATA 6Gb/s ports, 2 x Turbo M.2 slots
USB 3.1 Gen2	2 x USB 3.1 Gen2 (Type A+C)
USB 3.1 Gen1	8 x USB 3.1 Gen1
USB 2.0	6 x USB 2.0
LAN	Intel® I219-V Gigabit LAN
Audio	7.1-Channel High Definition Audio
Form Factor	ATX

## FEATURES



### Mystic Light RGB LED

Personalize your PC with 16.8 million colors / 17 effects, controlled in one click!



### Twin Turbo M.2

With 2 x M.2 slots. Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.



### Lightning USB 3.1 Gen2

Powered by the ASMedia ASM3142 USB 3.1 Gen2 controller, Lightning USB offers the fastest USB speeds up to 10 Gb/s.



### MSI GAMING LAN, powered by Intel

Enjoy the low latency online gaming with the ability to prioritize game traffic for the ultimate response times. With WIFI.



### MULTI-GPU

With Steel Armor PCI-E slot. Supports 2-Way AMD Crossfire™.



### VR Ready

Automatically optimizes your system for VR usage, pushing for maximum performance.



### Military Class 5

Latest evolution with high quality Japanese components for best protection and efficiency.



### Audio Boost

Reward your ears with studio grade sound quality for the most immersive audio experience.



### DDR4 Boost

Advanced technology to deliver pure data signals for the best gaming performance and stability.

## CONNECTIONS



- |                            |                            |
|----------------------------|----------------------------|
| 1. PS/2 GAMING Device Port | 2. USB 3.1 Gen1            |
| 3. Intel® Gigabit LAN Port | 4. Golden Audio Connectors |
| 5. USB 2.0 Ports           | 6. DVI-D Port              |
| 7. USB 3.1 Gen2            | 8. HDMI™                   |
| 9. Optical S/PDIF-Out      |                            |