




## SPECIFICATIONS

<b>WEIGHT (CARD)</b>	169g
<b>Suporte de formato de placa-mãe</b>	ATX / M-ATX / ITX
<b>Fator de forma gabinete</b>	Mid-Tower
<b>Nome</b>	MAG FORGE 112R
<b>Baías de Drive</b>	3 x 2.5" 2 x 2.5"/3.5"
<b>Dimensions</b>	120mm x 120mm x 25.6mm
<b>Dimensões</b>	409 x 214 x 485 mm / 16.1 x 8.43 x 19.9 inches
<b>Peso</b>	5.26 kg / 11.6 lbs
<b>Bearing Type</b>	Hydro-Dynamic Bearing
<b>Portas E/S</b>	2 x USB 3.2 Gen1 Type-A (5 Gbps) 1 x Audio-out 1 x Mic-in
<b>Rated Speed</b>	500 - 1800 ±15% RPM
<b>Slots de Expansão</b>	7
<b>Ventilador pré-instalado</b>	Front: 3 x 120 mm Rear: 1 x 120 mm
<b>Air Flow</b>	19.79 - 71.27 CFM
<b>Suporte ventilador</b>	Front: 3 x 120 mm / 2 x 140 mm Top: 2 x 120 mm / 2 x 140 mm Rear: 1 x 120 mm
<b>LAYOUT do radiador</b>	Front: 120 / 140 / 240 mm Top: 120 / 240 mm Rear: 120 mm
<b>Static Air Pressure</b>	0.16 - 2.09 mm-H2O
<b>Connector</b>	4-Pin PWM/DC
<b>Comprim.Máx GPU</b>	330 mm / 13 inches
<b>Life Expectancy</b>	MTTF 150,000 Hours (25°C)
<b>Comprim.Máx.Refrig.CPU</b>	160 mm / 6.3 inches
<b>Iluminação</b>	Front: 3 x ARGB Fan Rear: 1 x ARGB Fan
<b>Fonte de Alimentação</b>	ATX

## CONNECTIONS

## FEATURES



### Optimized Air Flow

Can install up to 6x system fans, providing ventilation and stable performance to the whole system.



### ARGB Fan included

Built-in ARGB fan with striking lighting and vivid lighting effects.



### Tool-Less Tempered Glass

Premium-grade 4mm thick tempered glass that guarantees window durability and viewing capability.



### Magnetic Filter

The magnetic dust filter on top is designed to give users an easy un-installing and cleaning experience.



### Mystic Light Sync

MSI Mystic Light provides you complete control of ARGB lighting of your PC in one software.




### 1 to 6 ARGB LED Control board

Bundle with 1 to 6 ARGB LED control board that gives you more ways to decorate your gaming rig.



### ARGB Fan included

Built-in ARGB fan with striking lighting and vivid lighting effects.



1. LED Switch Button
2. 2x USB 3.2 Gen1 Type A
3. Mic In
4. Audio Out
5. Reset Button
6. Power Button