MAG PANO 110R PZ

SMART IN SPACING





SPECIFICATIONS

| Support MB Form Factor | Regular: ATX / Micro-ATX / Mini-ITX Back-connect: ATX / Micro-ATX |
|---------------------------|---|
| Form Factor | Mid-Tower |
| Product Name | MAG PANO 110R PZ / WHITE |
| Drive Bays | 2 x 2.5" 2 x 3.5" 2 x 2.5"/3.5" combo |
| Dimension | 420 x 225 x 485 mm / 16.54 x 8.86 x 19.09 inches |
| I/O Ports | 1 x USB 20Gbs (Type-C) 2 x USB 5Gbs (Type-A) 1 x Audio-Out / Mic-in 1 x LED Button 1 x Power Button |
| Case Expansion Slots | 7 |
| Pre-install Fan | Side: 3 x 120 mm Rear: 1 x 120 mm |
| Fan Size Support | Top: 3 x 120 mm / 2 x 140 mm Front: NA Rear: 1 x 120 mm Side: 3 x 120 mm / 2 x 140 mm Bottom: 3 x 120 mm (Above the power shroud) |
| Maximum PSU Length | 200 mm / 7.87 inches |
| Maximum GPU Length | 400 mm / 15.75 inches |
| Maximum CPU Cooler Length | 160 mm / 6.30 inches |
| Radiator Layout | Top: 120 / 140 / 240 / 280 / 360 mm Front: NA Rear: 120 mm Side: NA Bottom: NA |
| Lightning | Side: 3 x ARGB Fan (Reverse Blades Fan) Rear: 1 x ARGB Fan |
| Power Supply | ATX |
| | |

FEATURES



Support Back-Connect Motherboard

Back-Connect PROJECT ZERO motherboards simplify cable management, providing a clear and aesthetic pleasing system setup.



Upgrade Airflow Layout

This model support maximizes up to 10 fans and a 360 mm radiator on top. The lower chamber, surrounded by vents further enhance heat dissipation for optimal performance.



270-Degree Display

The chassis features a 270-degree panoramic design with 3 mm tempered glass, offering an expansive view to showcase detailed components.



1 to 5 ARGB-FAN Control Board

This fan control board supports up to 5 x ARGB fans, allowing users to adjust the ARGB lighting effect with single one LED switch button.



Pre-build with Reverse Blades Fan

Pre-installed reverse blade fans on the side allow the unobstructed display of the ARGB fan's beauty without any interference from fan frames.

CONNECTIONS



PC CASE MAG PANO 110R PZ

SMART IN SPACING



- 1. 1 x USB 20Gbs (Type-C)
- 2. 2 x USB 5Gbs (Type-A)
- 3. Mic In/ Audio Out
- 4. LED Button
- 5. Power Button