



## SPECIFICATIONS

<b>Support MB Form Factor</b>	ATX / Micro-ATX / Mini-ITX
<b>Maximum GPU Height</b>	150 mm / 5.91 inches
<b>Case Form Factor</b>	Mid Tower
<b>Product Name</b>	MAG FORGE 321R AIRFLOW
<b>Drive Bays</b>	1 x 2.5" 2 x 2.5" / 3.5"
<b>Dimension</b>	472.5 x 210 x 498 mm / 18.60 x 8.26 x 19.60 inches
<b>Weight</b>	7.05 kg / 15.54lbs
<b>I/O Ports</b>	1 x USB 3.2 Gen 2x2 Type-C 2 x USB 3.2 Gen 1 Type-A 1 x Mic-in / Audio-out 1 x LED Switch
<b>Case Expansion Slots</b>	7
<b>Pre-install Fan</b>	Front: 3 x 120 mm Rear: 1 x 120 mm
<b>Fan Size Support</b>	Front: 3 x 120 mm / 2 x 140 mm Top: 3 x 120 mm / 2 x 140 mm Rear: 1 x 120 mm Side: 2 x 120 mm PSU Shroud: 2 x 120 mm
<b>Maximum PSU Length</b>	200 mm / 7.87 inches (without 2.5"/3.5" HDD tray installation)
<b>Maximum GPU Length</b>	390 mm / 15.35 inches
<b>Maximum CPU Cooler Length</b>	160 mm / 6.29 inches
<b>Radiator Layout</b>	Front: 120 / 140 / 240 mm Top: 120 / 240 / 280 / 360 mm Rear: 120 mm
<b>Lightning</b>	Front: 3 x ARGB Fan Rear: 1 x ARGB Fan
<b>Power Supply</b>	ATX
<b>Gross Weight</b>	8.35 kg / 18.41lbs

## CONNECTIONS

## FEATURES



### Optimized Air Flow

Up to 11 x system fans could be installed. Provides the whole system with ventilation for better stability



### ARGB Fan

Built-in ARGB fan with striking lighting and vivid lighting effects.



### Tempered Glass

Premium-grade 3mm thick tempered glass that guarantees window durability and viewing capability.



### 4-ARGB-Fan Control board

Bundle with 1 to 4 ARGB-fan control board that gives you more ways to decorate your gaming rig.



### Mystic Light Sync

MSI Mystic Light provides you complete control of ARGB lighting of your PC in one software.



### Magnetic Filter

The magnetic dust filter on top is designed to give users an easy un-installing and cleaning experience.



### USB 3.2 Gen 2x2 Type C

Built-in USB 3.2 Gen 2x2 Type-C offers 20Gbps transmission speed, combined with the convenience of its reversible design.



P C C A S E

## MAG FORGE 321R AIRFLOW

BEYOND THE POWER



1. Power Button
2. LED Switch Button
3. Audio Out / Mic In
4. 2 x USB 3.2 Gen 1 Type-A
5. 1 x USB 3.2 Gen 2x2 Type-C