



SPECIFICATIONS

Soporte de formato de placa madre	Regular: ATX / Micro-ATX / Mini-ITX Back-connect: ATX / Micro-ATX
Formato del gabinete	Mid-Tower
Producto	MAG PANO 130R PZ / WHITE
Peso	Black: 10 kg / 22.04 lbs White: 10 kg / 22.04 lbs
Puertos E/S	2 x USB 5Gbps (Type-A) 1 x USB 20Gbps (Type-C) 1 x Audio-Out / Mic-in 1 x Reset Button 1 x Power Button
Bahías para Drivers	Up to 3 x 2.5" SSD Up to 2 x 3.5" HDD (Maximum of 3 drives can be mounted at once, depending on configuration)
Slots de Expansión Gabinete	7
Distribución radiador	Top: 120 / 140 / 240 / 280 / 360 mm Front: N/A Rear: 120 mm Side: 120 / 240 / 360 mm Bottom: N/A
Soporte para ventilador	Top: 3 x 120 mm / 2 x 140 mm Front: N/A Rear: 1 x 120 mm Side: 3 x 120 mm Bottom: 3 x 120 mm (Above the power shroud)
Longitud máxima de la Fuente	180 mm / 7.09 inches
Longitud máxima de GPU	400 mm / 15.75 inches
Longitud máxima del Cooler de CPU	165 mm / 6.50 inches
Lightning	Rear: 1 x 120 mm ARGB Fan Side: 3 x 120 mm ARGB Fan (Reverse Blade Fan)
Peso bruto	Black: 8.37 kg / 18.45 lbs White: 8.37 kg / 18.45 lbs

CONNECTIONS

FEATURES



Support Back Back-Connect ATX Motherboard

Compatible with ATX PROJECT ZERO motherboards, allowing easy installation and streamlined cable management by routing cables through the rear.



Upgrade Airflow Layout

This model supports up to 10 fans and 360 mm radiator on top and side. The lower chamber also surrounded by vents further enhance heat dissipation for optimal performance.



Rotatable PCIe Bracket

One bracket, two orientations. A quick 90° rotation allows quick switching between horizontal and vertical GPU installations.



Dust Filter

Magnetic top and removable bottom dust filters enhance airflow while keeping your system clean, protecting internal components from dust buildup.



Pre build with Reverse Blades Fan

Installed reverse blade fans on the side allow the unobstructed display of the ARGB fan's beauty without interference.



1. 2 x USB 5Gbps (Type-A)
2. 1 x USB 20Gbps (Type-C)
3. 1 x Audio-Out / Mic-in
4. 1 x Reset Button
5. 1 x Power Button